

Reversing, Three Pole Contactors With AC Coil, Series CAU7 (Open type only)

I _e [A]		Ratings for Switching AC Motors (AC2 / AC3 / AC4)										Auxiliary Contacts per Contactor		Open Type	Catalog Number	Price
		kW (50 Hz)				UL/CSA HP (60 Hz)										
		230V	400V 415V	500V	690V	1 Ø		3 Ø								
AC-3	AC-1	230V	415V	500V	690V	115V	230V	200V	230V	460V	575V	NO	NC ③			
9	32	3	4	4	4	1/2	1 1/2	2	2	5	7-1/2	1	1	CAU7-9-22-*	338	
12	32	4	5.5	5.5	5.5	1/2	2	3	3	7-1/2	10	1	1	CAU7-12-22-*	409	
16	32	5.5	7.5	7.5	7.5	1	3	5	5	10	15	1	1	CAU7-16-22-*	451	
23	32	7.5	11	13	10	2	3	5	7-1/2	15	15	1	1	CAU7-23-22-*	491	
30	65	10	15	15	15	2	5	7-1/2	10	20	25	0	1	CAU7-30-02-*	553	
												1 ④	1	CAU7-30-22-*	597	
37	65	11	18.5/20	20	8.5	3	5	10	10	25	30	0	1	CAU7-37-02-*	640	
												1 ④	1	CAU7-37-22-*	684	
43	85	13	22	25	22	3	7-1/2	10	15	30	30	0	1	CAU7-43-02-*	710	
												1 ④	1	CAU7-43-22-*	754	
55	85	15	30	30	22	5	10	15	20	40	40	0	1	CAU7-55-02-*	797	
												1 ④	1	CAU7-55-22-*	841	
60	100	18.5	32	37	32	5	10	15	20	40	50	0	1	CAU7-60-02-*	895	
												1 ④	1	CAU7-60-22-*	939	
72	100	22	40	45	40	5	15	20	25	50	60	0	1	CAU7-72-02-*	1010	
												1 ④	1	CAU7-72-22-*	1054	
85	100	25	45	55	45	7-1/2	15	25	30	60	60	0	1	CAU7-85-02-*	1125	
												1 ④	1	CAU7-85-22-*	1169	
97	130	30	55	55	55	10	20	30	30	75	75	0	1	CAU7-97-02-*	1410	
												1 ④	1	CAU7-97-22-*	1454	



CAU7-9-22-120 reversing contactor



CAU7-43-22-120 reversing contactor

Includes:

- Line side coil terminations
- Mechanical and electrical Interlock ③
- Reversing power wiring ① (using Power Wiring Kit Cat.# CAUT7-PW...)
- Control wiring available; see footnote ②

Coil Codes ⑤

AC Coil Code	Voltage Range	
	50 Hz	60 Hz
24Z	24V	24V
120	110V	120V
208	~	208V
220W	200V-220V	208V - 240V
240	220V	240V
277	240V	277V
380	380V-400V	440V
480	440V	480V
600	550V	600V

Ordering Instructions

Specify Catalog Number	
Replace (*) with Coil Code	See Coil Codes on this page.

- ① For Reversing Contactors *without* power wiring add suffix "-LW" to catalog number and deduct the following amount:
 CAU7-9...23 deduct \$10
 CAU7-30...37 deduct \$12
 CAU7-43...55 deduct \$22
 CAU7-60...97 without power wiring not available
 Ex: CAU7-9-22-* becomes CAU7-9-22-***-LW**.
- ② For control wiring, add suffix **-CW** to catalog number and add \$20.
 Example: CAU7-9-22-* becomes CAU7-9-22-***-CW**.
- ③ The NC auxiliary contacts are supplied as part of the mechanical interlock (Cat.# CM7-02) and are used to electrically interlock the contactors.
- ④ The NO auxiliary contacts supplied are side mounted. Top mount NO auxiliary contacts must be special ordered. Contact your Sprecher+Schuh representative.
- ⑤ Other voltages available, see page A56. *Nonstandard coil voltages not listed here must be ordered and installed separately as renewal parts.*